

EML2 - £1/£2 DUAL COIN SLOTMETER



- Fully MID approved
- Two modes of operation: prepayment mode and timer mode
- Easy to read LCD display
- Two different coin or token values accepted
- Coin rejection chute
- Push button programming
- 100 Amp current rating
- Economy 7 operation (2 rates)
- Standing charge and debt collection features
- Built on the popular Emlite EMA base meter

The meter is fully approved in accordance with the Measuring Instrument Directive(MID). This highly functional meter may be used for resale of electricity or services.

Being MID approved this new meter meets all relevant OFGEM and EU registration in relation to the resale of electricity.

In electricity prepayment mode the meter provides options for one or two tariff operation, separately programmable standing charge and debt collection facilities.

Easy to use and program

The prepayment meter shows the current level of credit on the meters LCD display. This is complemented by the display information label which explains the symbols shown on the meter's display.

When the meter has run out of credit then the internal 100 amp breaker disconnects the energy supply and illuminates the red cross indicator. When coins are inserted the coin illuminator turns off and electricity supply is continued.

The consumption LED will blink to indicate energy consumption.

Programming manual included

The meter comes with an informative programming manual explaining in detail how to program the meter for the two modes of operation.

COINS

The EML2 as standard is supplied to accept £1 & £2 Coins. We supply meter able to accept any two coins including Euros.

TOKENS

If the meter is being installed not in a highly secure area then a token operated meter may be a great solution. The coin tokens sold by us can be used indefinitely. Unlike card metering with the on going cost of meter cards.

METER DIMENSIONS: Height: 280mm Width: 208mm Depth: 95mm

Electric Slotmeters London (ESL UK LTD)

37 Palestine Grove, Wimbledon, London, SW19 2QN

TEL: 02086468111

FAX: 02086468333

Email: eslukitd@btconnect.com